

L Number	Hits	Search Text	DB	Time stamp
1	682	(time adj domain) same spatial	USPAT	2002/09/13 14:23
2	38	eigen with filter\$3	USPAT	2002/09/13 14:23
3	0	((time adj domain) same spatial) and (eigen with filter\$3)	USPAT	2002/09/13 14:22
4	62	(time adj domain) same spatial	EPO; JPO; DERWENT; IBM_TDB	2002/09/13 14:23
5	21	eigen with filter\$3	EPO; JPO; DERWENT; IBM_TDB	2002/09/13 14:23
6	0	((time adj domain) same spatial) and (eigen with filter\$3)	EPO; JPO; DERWENT; IBM_TDB	2002/09/13 14:23

**Noise optimized eigenfilter design of time-domain equalizers for DMT systems**

Tkachenko, A.; Vaidyanathan, P.P. Communications, 2002. ICC 2002. IEEE International Conference on , Volume: 1 , 2002

Page(s): 54 -58

Design of a class of IIR eigenfilters with time- and frequency-domain constraints

Soo-Chang Pei; Chia-Chen Hsu; Peng-Hua Wang

Circuits and Systems II: Analog and Digital Signal Processing, IEEE Transactions on , Volume: 49 Issue: 2 , Feb. 2002

Page(s): 145 -151

Correlation and spatial sensitivity of eigenfilters for selective signal cancellation in multiple-listener environments

Bharitkar, S.; Kyriakakis, C. Signals, Systems and Computers, 2001. Conference Record of the Thirty-Fifth Asilomar Conference on , Volume: 2 , 2001

Page(s): 1578 -1582 vol.2

Variance-based spatial filtering in fMCG

Chen, M.; Wakai, R.T.; Van Veen, B.D. Engineering in Medicine and Biology Society, 2000. Proceedings of the 22nd Annual International Conference of the IEEE , Volume: 2 , 2000

Page(s): 956 -957 vol.2

Laguerre network design in complex domain

Masnadi-Shirazi, M.A.; Safdar, M. Electronics, Circuits and Systems, 2000. ICECS 2000. The 7th IEEE International Conference on , Volume: 1 , 2000

Page(s): 95 -98 vol.1

A frequency-domain eigenfilter approach for equalization in discrete multitone systems

Bo Wang; Adali, T. Signals, Systems, and Computers, 1999. Conference Record of the Thirty-Third Asilomar Conference on , Volume: 2 , 1999

Page(s): 1058 -1062 vol.2

Spatial signature estimation in cyclic cumulant domain and multiuser signal separation in uplink SDMA

Qinye Yin; Minli Yao Acoustics, Speech, and Signal Processing, 1999. Proceedings., 1999 IEEE International Conference on , Volume: 5 , 1999

Page(s): 2861 -2864 vol.5

Fast modal ABC's in the hybrid PEE-FDTD analysis of waveguide discontinuities

Kreczkowski, A.; Rutkowski, T.; Mrozowski, M.

IEEE Microwave and Guided Wave Letters [see also IEEE Microwave and Wireless Components Letters] , Volume: 9 Issue: 5 , May 1999

Page(s): 186 -188

A method for design of Mth-band filters

Wisutmethangoon, Y.; Nguyen, T.Q.

Signal Processing, IEEE Transactions on , Volume: 47 Issue: 6 , June 1999

Page(s): 1669 -1678

Embedded FIR generalized eigenfilters using test inputs

Coleman, J.O. Acoustics, Speech and Signal Processing, 1998. Proceedings of the 1998 IEEE International Conference on , Volume: 3 , 1998

Page(s): 1313 -1316 vol.3

Nonlinear phase Mth band filter and applications in filter bank design

Wisutmethangoon, Y.; Nguyen, T.Q. Signals, Systems & Computers, 1997. Conference Record of the Thirty-First Asilomar Conference on , Volume: 1 , 1997

Page(s): 696 -700 vol.1

Optical dispersion eigencompensators for high-speed long-haul IM/DD lightwave systems: computer simulation

Ngo, N.Q.; Binh, L.N.; Xianda Dai

Lightwave Technology, Journal of , Volume: 14 Issue: 10 , Oct. 1996

Page(s): 2097 -2107

Fast recursive eigensubspace adaptive filters

Strobach, P. Acoustics, Speech, and Signal Processing, 1995. ICASSP-95., 1995 International Conference on , Volume: 2 , 1995

Page(s): 1416 -1419 vol.2

Eigen analysis of series compensation schemes reducing the potential of subsynchronous resonance

Iravani, M.R.; Edris, A.-A.

Power Systems, IEEE Transactions on , Volume: 10 Issue: 2 , May 1995

Page(s): 876 -883

An efficient least-squares approach for the design of two-dimensional linear-phase nonrecursive filters

Sunder, S.; Ramachandran, R.P. Circuits and Systems, 1994. ISCAS '94., 1994 IEEE International Symposium on , Volume: 2 , 1994

Page(s): 577 -580 vol.2

Design of 1-D and 2-D IIR eigenfilters

Soo-Chang Pei; Jong-Jy Shyu

Signal Processing, IEEE Transactions on , Volume: 42 Issue: 4 , April 1994

Page(s): 962 -966

Unified eigenfilter approach: with applications to spectral/spatial filtering

Chen, T. Circuits and Systems, 1993., ISCAS '93, 1993 IEEE International Symposium on , May 1993

Page(s): 331 -334 vol.1

Unified Eigenfilter Approach: With Applications To Spectral/spatial Filtering

Tsuan Chen Circuits and Systems, 1993., ISCAS '93, 1993 IEEE International Symposium on , May 1993

Page(s): 331 -334

A unified framework for the least-squares design of linear-phase nonrecursive filters

Ramachandran, R.P.; Sunder, S. Circuits and Systems, 1993., Proceedings of the 36th Midwest Symposium on , 1993

Page(s): 480 -483 vol.1

A new method for multiple source detection and identification from array data using cumulants and its application to shock waves propagation

Gaeta, M.; Nikias, C.L. Higher-Order Statistics, 1993., IEEE Signal Processing Workshop on , 1993

Page(s): 235 -239

Design of two-dimensional FIR eigenfilters for sampling-structure conversion

Pei, S.-C.; Shyu, J.-J.

Circuits and Systems for Video Technology, IEEE Transactions on , Volume: 3 Issue: 2 , April 1993

Page(s): 158 -162

Design of IFIR eigenfilters

Chen, T.; Vaidyanathan, P.P. Circuits and Systems, 1991., IEEE International Symposium on , 1991

Page(s): 264 -267 vol.1

A computer program for designing linear phase FIR digital filters by eigen-approach

Pei, S.-C.; Shyu, J.-J. Circuits and Systems, 1989., IEEE International Symposium on , 1989

Page(s): 367 -370 vol.1

2D FIR eigenfilters

Nashashibi, A.; Charalambous, C. Circuits and Systems, 1988., IEEE International Symposium on , 1988

Page(s): 1037 -1040 vol.2

Copyright © 2002 IEEE -- All rights reserved

Correlation and Spatial Sensitivity of Eigenfilters for Selective Signal Cancellation in Multiple-Listener Environments

Sunil Bharitkar *Student Member, IEEE*, and Chris Kyriakakis *Member, IEEE*

Section: 7. Speech, Audio and image/video processing

Abstract: Selectively cancelling signals at specific locations within an acoustical environment with multiple listeners is of significant importance for home theater, automobile, teleconferencing, office, industrial and other applications. We have proposed the eigenfilter for selectively cancelling signals in one direction, while attempting to retain them at unintentional directions. In this paper we investigate the behaviour of the performance measure (i.e., the gain) for a vowel and an unvoiced fricative, when the listener moves his head, in an automobile type environment. We show that in such a situation, a large energy in the difference between the impulse responses at a listener's location may affect the gain substantially. Preliminary results also show that the gain is not significantly affected by the variations in the type of the speech signal.

I. INTRODUCTION

Integrated media systems are envisioned to have a significant impact on the way groups of people in remote locations communicate with each other. One of the critical elements that help enhance the suspension of disbelief required to convince people that they are truly in the same environment is sound. While a great deal of ongoing research has focused on the problem of delivering high quality sound to a single listener, the problem of delivering the appropriate audio signals to multiple listeners in the same environment has not yet been adequately addressed.

In previous work [1], [2], [3] we focused on presenting an audio signal at a selected direction in a room, while simultaneously minimizing the signal power at another direction. For example, in home theater or television viewing applications a listener in a specific location in the room may not want to listen to the audio signal being transmitted, while another listener at a different location would prefer to listen to the signal. Consequently, if the objective is to keep one listener in a region with a reduced sound pressure level, then one can view this problem as that of signal cancellation in the direction of that listener. Similar applications

arise in the automobile (e.g., when only the driver would prefer to listen to an audio signal), or any other environment with multiple listeners in which only a subset wish to listen to the audio signal.

An eigenfilter for selective signal cancellation is designed by optimizing an objective function as shown in Section 2. Section 3 summarizes some properties of eigenfilters for stationary signals. In Section 4 we show that the performance function is affected for certain changes in the responses (such as head movements) in a simulated automobile type environment. We confirm these results for simple speech signals, (i) an unvoiced fricative /S/ as in *gat*, (ii) a vowel /AE/ as in *bat*. Section 5, presents preliminary results demonstrating that the gain is not significantly affected when an eigenfilter is designed for one type of speech signal, but a radically different speech signal is presented for cancellation. We conclude this paper in Section 6, and suggest some future directions.

II. THE EIGENFILTER FOR SELECTIVE SIGNAL CANCELLATION

An objective criterion is designed for maximizing the difference in signal power between two different listener locations that have different source-receiver response characteristics. For simplicity we assume that the listeners can be modeled as point receivers. The method can also be extended to take into account ear spacing and head-related transfer function effects. The filter, known as the eigenfilter that is derived by optimizing the objective function, operates on the raw signal before the resulting signal is linearly transformed by the room responses in the direction of the listeners. Such filters aim at increasing the relative gain in signal power between the two listeners with some associated tradeoffs such as: (i) spectral distortion that may arise from the presence of the eigenfilter, and (ii) the sensitivity of the filter to the length of the room impulse response (reverberation), (iii) perceptual coloration, and (iv) sensitivity to spatial variations in the room responses (due to listener head movements). In this paper we focus on the sensitivity issue in a space that has the approximate dimensions of an automobile interior as an example of where this approach could be implemented. We also investigate the gain variations with changes in the excitation signal.

A. Determination of the Eigenfilter

Under our assumption of modeling the listeners as point receivers we can set up the problem as shown in Fig. 1,

The authors are with the Immersive Audio Laboratory, Integrated Media Systems Center, University of Southern California, 3740 McClintock Avenue, Los Angeles, CA 90089-2564.

This research has been funded by the Integrated Media Systems Center, a National Science Foundation Engineering Research Center, Cooperative Agreement No. EEC-9529152.

where $w_k; k = 0, 1, \dots, M-1$ represents the coefficients of the finite impulse response filter to be designed. During the design phase we assume that the listeners are stationary. The listening model is then simply

$$y_i(n) = h_i(n) \otimes \sum_{k=0}^{M-1} w_k x(n-k) + v_i(n) \quad i = 1, 2 \quad (1)$$

where \otimes represents the convolution operation. With this background, we view the signal cancellation problem as a gain maximization problem (between two arbitrary listeners), we can state the performance criterion as,

$$J(n) = \max_{\underline{w}} \frac{1}{2} \left(\frac{\sigma_{y_2(n)}^2}{\sigma_{v_2(n)}^2} \right) - \frac{\lambda}{2} \left(\frac{\sigma_{y_1(n)}^2}{\sigma_{v_1(n)}^2} - \psi \right) \quad (2)$$

in which we would like to maximize the signal to noise ratio (or signal power) in the direction of listener 2, while keeping the power towards listener 1 constrained at $10\psi_{dB}/10$ (where $\psi_{dB} = 10 \log_{10} \psi$). In (2), $\sigma_{y_i(n)}^2 / \sigma_{v_i(n)}^2$ denotes the transmitted signal to ambient noise power at listener R_i with $y_i(n)$ as defined in (1). The quantity λ is the well known Lagrange multiplier.

It can be easily shown, under equal ambient noise, that the optimal filter, \underline{w}^* , is an eigenfilter given by

$$\begin{aligned} \underline{w}^* &= \underline{e}_{\lambda_{\max}[B^{-1}A]} \\ A &= \sum_{p=0}^{S-1} \sum_{q=0}^{S-1} h_2(p) h_2(q) \underline{R}_z(p, q) \\ B &= \sum_{p=0}^{L-1} \sum_{q=0}^{L-1} h_1(p) h_1(q) \underline{R}_z(p, q) \end{aligned} \quad (3)$$

where, $\underline{e}_{\lambda_{\max}[B^{-1}A]}$ denotes the eigenvector corresponding to the maximum eigenvalue λ_{\max} of $B^{-1}A$.

The performance is the gain G_{dB} expressed as,

$$\begin{aligned} G_{dB} &= 10 \log_{10} \frac{\sigma_{y_2(n)}^2}{\sigma_{v_1(n)}^2} \\ &= 10 \log_{10} \frac{\underline{w}^{*T} A \underline{w}^*}{\underline{w}^{*T} B \underline{w}^*} \end{aligned} \quad (4)$$

Fundamentally, by casting the signal cancellation problem as a gain maximization problem, we aim at introducing a large gain of Q dB between two listeners, R_1 and R_2 . This Q dB gain is equivalent to virtually positioning listener R_1 at a distance which is $\sqrt{10^{Q/10}}$ times the distance of listener R_2 from a fixed sound source*.

III. SOME PROPERTIES OF EIGENFILTERS

A couple of interesting properties of the proposed eigenfilter under wide-sense stationary (WSS) assumptions are restated below.

*Strictly speaking, in the free field, the gain based on the inverse square law, is expressed as, $Q = 10 \log_{10} r_1^2 / r_2^2$ (dB), where r_1, r_2 are the radial distances of listeners R_1 and R_2 from the source.

Property 1 : For a WSS processes $x(n)$, and $y(n)$ with finite variances, the matrix $\underline{R}_z(p, q)$ is toeplitz, and the gain (4) can be expressed as,

$$G_{dB} = 10 \log_{10} \frac{\int_{-\pi}^{\pi} |W^*(e^{j\omega})|^2 |H_2(e^{j\omega})|^2 S_x(e^{j\omega}) d\omega}{\int_{-\pi}^{\pi} |W^*(e^{j\omega})|^2 |H_1(e^{j\omega})|^2 S_x(e^{j\omega}) d\omega} \quad (5)$$

where, $r_x(k) \in \underline{R}_z(k)$ and $S_x(e^{j\omega})$ form a fourier transform pair, and $h_1(n)$ and $h_2(n)$ are stable responses. Moreover, since we are focusing on real processes in this chapter, the matrix $\underline{R}_z(k)$ is a symmetric matrix, with

$$r_x(k) = r_x(-k) \quad (6)$$

Property 2 (Linear phase) : The optimal eigenfilter (4) is a linear phase FIR filter having a constant phase and group delay, or a constant group delay.

IV. SENSITIVITY TO SPATIAL VARIATIONS OF LISTENERS

The goal in this experiment is to observe the robustness of the designed optimal eigenfilter to variations in room responses. For the present situation, we generated synthetic room responses, at the direction of the two listeners, using the image method [4] for an automobile enclosure (dimensions of $2m \times 2m \times 2m$). The relative locations of the source and the two listeners is shown in Fig. 2, where a single source is assumed to be operating below and to the left of the driver (e.g., a speaker located on the driver side door). Listener 2 is assumed to be the driver, whereas listener 1 is assumed to be the passenger for designing the eigenfilter. The normal (nominal) positions of the driver and passenger are denoted by an asterisk. An eigenfilter was designed for these two locations (having different responses). A set of four responses were also synthesized around each of the listeners head, depicting head movements of the listeners (indicated by circles). Two eigenfilters were designed. The first design involved an unvoiced fricative /S/ as an input to the automobile enclosure (shown in Fig. 3), whereas the second design involved a vowel /AE/ as an input to the eigenfilter (shown in Fig. 4). Once the eigenfilter was determined for the nominal head locations, the gain (4) was obtained for the nominal positions, as well as for positions corresponding to the head variations (while keeping the eigenfilter fixed). Ideally, it is preferred that the gain changes are negligible with listener variations. The order M of the eigenfilter was set at 100. We are currently investigating the perceptual effects of filter length on sound quality and will report those results in the near future.

A. Unvoiced Fricative /S/

The gain (dB) matrix as a function of spatial variations is given below. In the matrix, a gain at the i -th row and the j -th column provides a gain at an i -th location of the driver head against the j -th location of the passenger head around the nominal position ($i = j = 1$ indicates the gain at nominal locations of the head for which the eigenfilter was designed). The nominal positions of the driver and

passenger head are marked by an asterisk. The numbers in the parenthesis depict the energy in the difference between the room responses for nominal positions and room responses for head variations.

	1* (0%)	2 (0%)	3 (82%)	4 (8.%)	5 (59%)
1*(0%)	10.8	10.8	-.57	6.7	0.5
2 (10.9%)	11.7	11.7	.37	7.6	1.4
3 (30.3%)	12	12	.6	.8	1.6
4 (30.3%)	12	12	.6	7.8	1.6
5 (10.9%)	11.7	11.7	.37	7.6	1.4

B. Vowel /AE/

The gain matrix for this case is given below:

	1* (0%)	2 (0%)	3 (82%)	4 (8.%)	5 (59%)
1*(0%)	11.3	11.3	-.8	6.8	.44
2 (10.9%)	12.4	12.4	.17	7.8	1.4
3 (30.3%)	12.7	12.7	.5	8.1	1.8
4 (30.3%)	12.7	12.7	.5	8.1	1.8
5 (10.9%)	12.4	12.4	.17	7.8	1.4

The largest changes in the gain occur when the passenger head location varies. This is mapped in Fig. 5, which depicts the energy in the difference between the room responses for nominal positions and room responses for head variations[†]. In summary largest changes in the gain occur for large energy differences between room responses at the passengers (listener 1) head. This seems intuitive, since the driver's response has a dominant direct field component which is not substantially affected due to the closeness of the driver to the source. The passenger's response has dominant reflective components which vary significantly with variations in the head locations.

V. SENSITIVITY TO VARYING EXCITATION SIGNALS

As can be seen from (4), the gain is affected by the variations in the A and B matrices. One cause for the changes in the gain, besides due to the spatial response variations discussed above, is due to the differences in signals applied to the eigenfilter for cancellation. The differences in the signals cause differences in the second order statistics, thereby affecting the gain. One goal in this preliminary experiment is to observe the robustness of the designed optimal eigenfilter to differences in the excitation signal applied to the eigenfilter for cancellation. For the present situation, we used the signals from the previous section. That is, we designed an eigenfilter (again $M = 100$) for the unvoiced fricative having a correlation function shown in Fig. 7(a), then applied the vowel (which has a radically different correlation function as shown in Fig. 7(b)) for signal can-

[†]The energy difference between room responses h_1 and h_2 is given by $\|h_1 - h_2\|^2 = \frac{1}{2\pi} \int_{-\pi}^{\pi} |H_1(e^{j\omega}) - H_2(e^{j\omega})|^2 d\omega$.

cellation, and computed the gain when the head positions changed. We also observed the effects on the gain when we combined the two signals as shown in Fig. 6, with the corresponding correlation function depicted in Fig. 7(c). The results are presented below for the vowel presentation, once the eigenfilter was designed for the unvoiced fricative (again, the normal (nominal) positions of the driver and passenger are denoted by an asterisk).

	1* (0%)	2 (0%)	3 (82%)	4 (8.%)	5 (59%)
1*(0%)	10.5	10.5	-2.08	5.5	.8
2 (10.9%)	11.62	11.62	-.9	6.6	1.9
3 (30.3%)	12.52	12.52	-.07	7.5	2.8
4 (30.3%)	12.52	12.52	-.07	7.5	2.8
5 (10.9%)	11.62	11.62	-.9	6.6	1.9

Comparing the above table with the first table in the Section IV, we see that the gain is not significantly affected due to this new presentation. The results in the above table do not change much even for the combined vowel-fricative presentation, after the eigenfilter is designed with the unvoiced fricative, since the correlation function (Fig. 7(c)) is not much different than for the vowel case (Fig. 7(b)).

VI. CONCLUSIONS

In this paper we investigated the robustness of the eigenfilter to changes in head locations of two listeners (i.e., changes in the responses at the two listeners) in an automobile type enclosure for simple speech signals, in terms of the gain. We observed that the performance is affected largely due to the passenger (listener 1) head movements than the driver head movements. We believe that this is because of larger energy in the difference between room responses corresponding to head movements and nominal responses. We plan to use perturbation theory to further investigate and quantify this behavior. Future research will also be directed to more complex signals, and perceptual aspects of designing eigenfilters (i.e., gain-perceptual coloration tradeoffs).

We also performed a preliminary experiment into the robustness of the eigenfilter to varying excitation signals having different correlation function. We see, that the gain is quite stable despite differences in the correlation functions between a newly presented speech sequence and the original speech sequence (on which the eigenfilter was designed).

REFERENCES

- [1] S. Bharitkar and C. Kyriakakis, "Selective Signal Cancellation for Multiple-Listener Audio Applications: An Information Theory Approach," *Proc. IEEE Conf. on Multimedia*, New York, July 2000.
- [2] S. Bharitkar and C. Kyriakakis, "Eigenfilters for Audio Signal Cancellation," *Proc. IEEE International Symposium on Intelligent Signal Processing and Communication Systems*, Hawaii, November 2000.
- [3] S. Bharitkar and C. Kyriakakis, "Selective Signal Cancellation For Multiple-Listener Audio Applications Using Eigenfilters,"

IEEE Trans. on Multimedia, conditionally accepted with revisions.

- [4] J. B. Allen and D. A. Berkley "Image method for efficiently simulating small-room acoustics," Journal of the Acoustical Society of America vol. 65, pp. 943-950, 1979.




Fig. 1. The source-two listener model.




Fig. 2. An automobile enclosure with a source and a driver and passenger.




Fig. 3. Unvoiced fricative speech signal /S/ as in sat.




Fig. 4. Vowel /AE/ as in bat




Fig. 5. Energy in the difference between room responses corresponding to head movements and nominal responses.




Fig. 6. Combined signal /S//AE/.




Fig. 7. First 301 samples of the correlation function for (a) unvoiced fricative /S/ (noise-like sequence), (b) vowel /AE/ (quasi-periodic sequence), (c) combined fricative-vowel sequence /S//AE/